



Official Tech Documents
The better way to get your HotBrick product up and running

Firewall HotBrick LB-2 / LB-2 VPN / VPN 800/2

Users Guide

Specific LB-2 / LB2 VPN / VPN 800 setups for most major ISPs

USA

7243 NW 54th Street
33166
Miami, FL
www.hotbrick.com
support@hotbrick.com

EUROPE

Generatorstraat 26
Hengelo (Ov), 7556 RC
Amsterdam - Netherlands
www.hotbrick.nl
support@hotbrick.nl

BRAZIL

Francisco Tramontano, 100
05686-010
São Paulo/SP
www.hotbrick.com.br
suporte@hotbrick.com.br

USA

7243 NW 54th Street
Miami, FL 33166
www.hotbrick.com
support@hotbrick.com

EUROPE

Generatorstraat 26
Hengelo (Ov), 7556 RC Amsterdam
Netherlands
www.hotbrick.nl

BRAZIL

Francisco Tramontano, 100
05686-010 – São Paulo/SP
www.hotbrick.com.br
suporte@hotbrick.com.br

Specific LB-2/LB2 VPN/ VPN 800 setups for most major ISPs

This guide was constructed to aid you through all types of configurations used by most major ISPs, and set them up on your LB-2, LB-2 VPN, or VPN 800

Bell South

Connection Type: PPPoE

Bell South uses the PPPoE protocol which requires you to input a user name and password. If you used any software to connect to the internet please uninstall it now as you will no longer need it. Once you have done that, login to the LB2/LB2 VPN/VPN 800 WAN Router by going to <http://192.168.1.1> using your favorite web browser. Set the connection type to PPPoE and input your user name and password into this PPPoE field, leave PPTP unchecked. Press the Submit button at the bottom of the page and you are done. Also, set the Echo Retry to 90 seconds under Advanced Port, Port Options menu.

Comcast

Connection Type: Dynamic IP

During the installation of your cable internet services, the installer should have paperwork with your registration information, copy down MAC address or Adapter Address from that a piece of paper. If you do not have this information, you can find out your MAC address by going to Start>Run, type in CMD and press enter. In the Command Prompt enter ipconfig/all and write down your MAC address. Once you have done that, login to the LB2/LB2 VPN/VPN 800 WAN Router by going to <http://192.168.1.1> using your favorite web browser. Set the Connection type as Dynamic IP and scroll down to Optional. In the MAC address field, type in that MAC address separated by hyphens. (Example: 0F-0F-0F-0F-0F-0F). Press the Submit button at the bottom of the page and you are done.

Cox

Connection Type: Dynamic IP

During the installation of your cable internet services, the installer should have paperwork with your registration information. The next step is to copy down the Domain Name from that piece of paper. You may also call Cox to find out your Domain name. Once you have done that, login to the LB2/LB2 VPN/VPN 800 WAN Router by going to <http://192.168.1.1> using your favorite web browser. Set your connection type as Dynamic IP and scroll down to Optional. In the Domain Name field enter your Domain Name. Press the Submit button at the bottom of the page and you are done.

Earthlink

Connection Type: PPPOE

Earthlink uses the PPPoE protocol which requires you to input a user name and a password. If you used any software to connect to the internet please uninstall it now as you will no longer need it. Once you have done that, login to the LB2/LB2 VPN/VPN 800 WAN Router by going to

USA

7243 NW 54th Street
Miami, FL 33166
www.hotbrick.com
support@hotbrick.com

EUROPE

Generatorstraat 26
Hengelo (Ov), 7556 RC Amsterdam
Netherlands
www.hotbrick.nl

BRAZIL

Francisco Tramontano, 100
05686-010 – São Paulo/SP
www.hotbrick.com.br
suporte@hotbrick.com.br

<http://192.168.1.1> using your favorite web browser. Set the connection type to PPPoE and input your user name and password into the PPPoE field leave PPTP unchanged. Press the Submit button at the bottom of the page and you are done.

SBC

Connection Type: PPPoE

SBC uses the PPPoE protocol which requires you to input a user name and password. If you used any software to connect to the internet please uninstall it now, as you no longer need it. Once you have done that, login to the LB2/LB2 VPN/VPN 800 WAN Router by going to <http://192.168.1.1> using your favorite web browser. Set the connection type to PPPoE and input your user name and password into the PPPoE field, leave PPTP unchecked and press the Submit button at the bottom of the page and you are done.

Road Runner

Connection Type: Dynamic IP

During the installation of your Cable internet services, the installer should have paperwork with your registration information, copy down Domain Name from that piece of paper. You may also call Road Runner to find out your Domain Name. Once you have done that, login to the LB2/LB2 VPN/VPN 800 WAN Router by going to <http://192.168.1.1> using your favorite web browser. Set your connection type as Dynamic IP and scroll down to Optional. In the Domain Name field, enter your Domain Name. Press the submit button at the bottom of the screen and you are done.